

Analogue Addressable Base Sounder

YBO-BS



Features

- ▶ Loop Powered with Single Loop Address - addressed automatically by Control Panel or via the TCH-B100 Hand Held Programmer
- ▶ Variable Sound Output
50 ~ 98 dB(A) (± 2 dB(A)) output at 1 metre
- ▶ Fits Hochiki Standard or Isolator Base and supports ESP Sensors, Addressable Beacons and Addressable Remote Indicator
- ▶ 51 User-Selectable Tones (all tones EN54-3 compatible)
- ▶ Auto-Shutdown feature prevents noise-pollution
- ▶ Approved by LPCB & VdS
- ▶ Also available in white
- ▶ SIL Level 2 approved variants available

Description

Model YBO-BS is an addressable loop powered Base Sounder innovatively designed to give a range of tones and volumes with a maximum output of up to 98 dB(A) (± 2 dB(A)) with low current consumption. The unit is designed to fit to the Standard Base (YBN-R/3) or the Isolator Base (YBO-R/SCI - from Batch Number 6044) and can be fitted with any of the ESP Range of Sensors, Beacons or Remote Indicators. The unit can also be converted into a wall sounder with the simple addition of a Cap (SI/CAP). The sounder is Ingress Protection rated to IP21 and for internal use only. An Auto-Shutdown feature allows the user to set a fixed time within which the sounder will operate, before automatically silencing itself, cutting noise pollution.

Specification

Ordering Codes	YBO-BS / YBO-BS(WHT) SI/CAP
Operating Voltage	17 ~ 41 VDC
Low Power Mode (typ)	40 μ A
Quiescent Current (typ)	150 μ A
Sounding Current (typ)	0.8 mA (50 dB(A) @ 1 m) ~ 16 mA (98 dB(A) @ 1 m)
Sound Output (at 1 metre)	50 ~ 98 dB(A) (± 2 dB(A)) @ 24 VDC or above (EN54-3 compliant)
Number of Tones	51
Tone Frequency Range	300 Hz ~ 2850 Hz
Operating Temperature Range	-10 °C to +50 °C
Storage Temperature Range	-30 °C to +70 °C
Maximum Humidity	95% RH - Non Condensing (at 40 °C)
Colour / Case Material	Ivory or white / PC+PS+GF5
Ingress Protection Rating	IP21
Weight (g) / Dimensions (mm)	112 / H113 x W113 x D43
Base Fixing Centres (mm)	48 ~ 74

Note: Although the TCH-B100 Hand Held Programmer will allow addresses between 128 and 254 to be programmed into the YBO-BS, addresses 1 to 127 ONLY should be used.

Hochiki Europe (UK) Ltd. reserves the right to alter the specification of its products from time to time without notice. Although every effort has been made to ensure the accuracy of the information contained in this document it is not warranted or represented by Hochiki Europe (UK) Ltd. to be a complete and up-to-date description.